

User Guide

PowerPod-10

Ultra Compact 35W SuperSpeed™ Power Bank with Built-In USB-C Cable

Introduction

Charge up and conquer the day with PowerPod-10 a 10000mAh power bank that also has a built-in USB-C cable. Additionally, this versatile power bank also features a 35W USB-C Power Delivery port and an 18W QC 3.0 USB-A port. The built-in multi-protection system combines high-voltage protection, over-current protection, over-charging protection, and more to ensure safe charging for all your connected devices. The smart LED screen keeps you informed on the charge left on your power bank. With convenience, portability, and reliability PowerPod-10 is an ideal accessory for modern living.

Packaging Contents

- PowerPod-10
- User Guide
- Charging Cable

Specifications

- Battery Capacity: 10000mAh, 3.7V/37Wh
- Battery Type: Lithium-ion
- USB-C Input: 5V/3A, 9V/3A, 12V/2.5A, 15V/2A, 20V/1.75A
- USB-C Output: 5V/3A, 9V/3A, 12V/2.5A, 15V/2A, 20V/1.75A
PPS 3.3-11V/3A
- USB-A Output: 5V/3A 9V/2A, 12V/1.5A
- USB-C Cable Input: 5V/3A, 9V/3A, 12V/2.5A, 15V/2A, 20V/1.75A
- USB-C Cable Output: 5V/3A, 9V/3A, 12V/2.5A, 15V/2A, 20V/1.75A
PPS 3.3-11V/ 3A
- Total Output: 35W

Features

- **Built-In USB-C Cable:** Forget the hassle of carrying extra cables as PowerPod-10 features a built-in USB-C Connector cable.
- **Power Loaded Battery:** PowerPod-10 boasts a powerful 10000mAh lithium-ion backup battery, so you can keep your devices powered up, anywhere, anytime.
- **35W Power Delivery Port:** PowerPod-10 delivers blazing-fast power to your USB-C power delivery-supported devices like smartphones and tablets.
- **Quick Charge 3.0:** This ultra-fast charging power bank also boasts a USB Quick Charge 3.0 port that provides 18W ultimate fast charge for compatible devices.
- **Automatic Voltage Regulation:** PowerPod-10 features Automatic Voltage regulation that offers the optimum charge to your connected devices.
- **Multi Protect System:** PowerPod-10 ensures safe and dependable charging, as it features over-charging and high-voltage protection.
- **Smart LED Screen:** Featuring an LED screen, it will keep you informed on the charge left on your PowerPod-10 power bank.

- **Ultra-Compact Design: Lightweight and portable enough to put in your pocket, place in your bag, or use on the go.**

Precautions

Please read all safety instructions and warnings thoroughly before using this product. Improper use of this product may result in damage to this or attached products.

1. Do not disassemble the backup battery or attempt to fix it.
2. Please charge this product with a charger approved by the local safety standards in case of danger or damage. Kindly use the original charging cable provided to charge the product.
3. Do not attempt to replace any part of this Backup battery or battery inside.
4. Please choose an appropriate charger for recharging this product and suitable cables when charging other devices.
5. Please ensure some supervision is in progress when recharging this product, do not charge this product without any care.
6. Please remove the cable when you are done recharging this product or finished charging for any other device to preserve the product integrity.
7. Do not crush, puncture, dispose of in fire, short the contacts or expose the battery to water or other liquids.
8. Do not connect input and output in reverse.
9. Do not store or use the battery in a high-temperature environment, including intense sunlight or heat.
10. Do not charge any device or recharge this product in places that may affect its heat dissipation, such as pants pockets, enclosed bags, beds or couches. Ensure this product is not under any cover when operating. When charging other devices for prolonged periods, do not stack any device on top of this product, or it might affect its heat dissipation.
11. Avoid drops, bumps, abrasions, and impacts.
12. If there is any reason to believe that there is damage to the battery, discontinue use immediately.
13. If you find that the battery is too hot, is emitting an odor, is deformed, punctured, or exhibits any suspicious or abnormal behavior, discontinue use immediately and contact our customer service.
14. Always charge this product before extended storage.

Appearance & Interface Description

1. LED Screen
2. USB-C Input/Output Port
3. Power Button
4. USB-C Connector Cable
5. USB-A Output Port

Operation Instructions:

1. **Checking the remaining power left in PowerPod-10 backup battery.**
 - To view the remaining power left, press the power button once and view the Battery Level on the LED Screen Display.
2. **Charging PowerPod-10 backup battery**
 - Connect one end of the USB-C Cable to PowerPod-10 or connect the Built-in USB-C Cable of PowerPod-10 to a desktop/laptop or a USB Power Adapter.
3. **Charging USB chargeable devices using PowerPod-10**
 - Plug the USB cable into the USB/USB-C output port on PowerPod-10 and the other end into the device.
 - Plug the built-in USB-C Connector cable into your device as required.